

FACILITIES FOR INTRASTATE ACCESS

EXPLANATION OF ABBREVIATIONS (Cont'd)

OPS – Off-Premises Station
PBX – Private Branch Exchange
PCM – Pulse Code Modulation
POT – Point of Termination
PSTN – Public Switched Telephone Network
PVU – Percent VoIP Usage

RMC – Recurring Monthly Charge
rms – root-mean-square

SCFA – Secondary Connecting Facility Assignment
SF – Single Frequency
SRL – Singing Return Loss
STR – Switched Transport Rate

TDCF – Total Day Conversion Factor
TDM – Time Division Multiplexing
TFC – Toll Free Code
TLP – Transmission Level Point
TV – Television

UL – Under Utilization Liability

VG – Voice Grade
VoIP – Voice over Internet Protocol

V&H – Vertical & Horizontal
WA – Wideband Analog
WATS – Wide Area Telecommunications Service

(N)

FACILITIES FOR INTRASTATE ACCESS

3. ORDERING OPTIONS FOR FIA (Cont'd)

3.2 Access Service Request (Cont'd)

3.2.2 ASR Modifications

The customer may request a modification of its ASR prior to the service date. The Telephone Company will make every effort to accommodate a requested modification when it is able to do so with the normal work force assigned to complete such an ASR within normal business hours. If the modification cannot be made with the normal work force during normal business hours, the Telephone Company will notify the customer. If the customer still desires the ASR modification, the Telephone Company will schedule a new service date. All charges for ASR modifications will apply on a per occurrence basis. Where a new ASR may be required the appropriate charges in other sections of this tariff will be applicable.

Any increase in the number of Switched Access lines for FGA or BSA-A; trunks or BHMCs for FGB, FGC, FGD, BSA-B, BSA-C, BSA-D and SAC Access Service and Special Access circuits will require the issuance of a new ASR for the incremental capacity.

(A) Service Date Change Charge

ASR service dates may be changed, however a Service Date Change Charge will apply for each service date change after the Plant Test Date on the ASR.

For Switched Access, the new service date may not exceed the original service date by more than 30 calendar days. If the requested service date is more than 30 calendar days after the original service date, the ASR will be canceled by the Telephone Company and cancellation charges in 3.2.6 will apply. The ASR will be reissued with the new service date.

For Special Access, except as specified below, the new service date may not exceed the original service date by more than 30 calendar days. If the requested service date is more than 30 calendar days after the original service date, the ASR will be canceled by the Telephone Company. Cancellation charges in 3.2.6 will apply and the ASR will be reissued with the new service date unless the customer indicates that billing for the service is to commence as in 3.2.6(A).

With the agreement of the Telephone Company, a new service date may be established that is prior to the original service date and the provisions in (E) will apply in addition to the Service Date Change Charge. The applicable charge is:

	<u>Rate</u>
Service Date Change Charge	
CenturyTel of Missouri	\$26.21

(N)

FACILITIES FOR INTRASTATE ACCESS

SECTION 4 TABLE OF CONTENTS (Cont'd)

4.	<u>SWITCHED ACCESS (Cont'd)</u>	<u>Sheet</u>
4.2	<u>Description of Switched Access (Cont'd)</u>	
	4.2.5 End Office Services Optional Arrangements (Cont'd)	
	(R) Up to 7 Digit Outpulsing of Access Digits to the Customer	110
	(S) Band Advance Arrangement	110
	(T) FGD and BSA-D Switched Access with 950-XXXX Access	111
	(U) Operator Assistance for SAC Access Services	111
	(V) Switched Access Interface	111
	(W) (Reserved for Future Use)	117
	(X) (Reserved for Future Use)	117
	(Y) Switched Data Service	117
	(Z) (Reserved for Future Use)	118
	(AA) Signaling System 7 (SS7) Out of Band Signaling	118
	(AB) Calling Party Number (CPN) Parameter	118
	(AC) Carrier Selection Parameter (CSP)	119
	(AD) Charge Number (CN) Parameter	119
	(AE) Tandem Switch Signaling	119
	(AF) Tandem Access Sectorization	119.1
	(AG) Carrier Identification Parameter (CIP)	119.1
	(AH) Flexible Automatic Number Identification (FLEX ANI)	119.2
	4.2.6 Call Restriction and Code Screening Reports	120
	4.2.7 Installation and Acceptance Testing of Switched Access	120
	4.2.8 Provision of Design Layout Report	120
	4.2.9 Network Management	120
	4.2.10 (Reserved for Future Use)	121
	4.2.11 TFC Customer Identification Function	121
	4.2.12 900 Customer Identification Function	121
	4.2.13 Design and Routing of Switched Access	121
	4.2.14 Provision of Switched Access Performance Data	122
	4.2.15 Transmission Performance	122
	4.2.16 Design Blocking Probability	123
	4.2.17 Special Facilities Routing	124
	4.2.18 Information Surcharge	124
	4.2.19 TFC Data Base Query Charge	125
	4.2.20 500 Customer Identification Function	125
	4.2.21 Tandem Switch Signaling	125
	4.2.22 Basic Service Elements (BSEs)	125.1
4.3	<u>Obligations of the Customer</u>	126
	4.3.1 On and Off-Hook Supervision	126
	4.3.2 ASR Requirements	126
	4.3.3 Jurisdictional Determination	126
4.4	<u>Payment Arrangements and Credit Allowances</u>	128
	4.4.1 (Reserved for Future Use)	128
	4.4.2 Cancellation of Applications	128
	4.4.3 Credit Allowances	128

(T)
|
(T)

(T)

(T)

FACILITIES FOR INTRASTATE ACCESS

SECTION 4 TABLE OF CONTENTS (Cont'd)

4.	<u>SWITCHED ACCESS (Cont'd)</u>	<u>Sheet</u>
4.5	<u>Rate and Charge Regulations</u>	128
4.5.1	Rate Elements	128
4.5.2	Rate Regulations	129
	(A) Types of Rates and Charges	129
	(1) Usage Rates	129
	(2) Flat Rated	129
	(3) Nonrecurring Charges	129.1
	(B) (Reserved for Future Use)	133
	(C) (Reserved for Future Use)	133
	(D) (Reserved for Future Use)	133
	(E) Change of Switched Access Type	133
	(F) Moves	133
	(1) Same CDL	134
	(2) A Different CDL	134
	(G) Signaling System 7 (SS7) Out of Band Signaling	134
	(H) TFC Data Base Query Service	134
	(I) Network Blocking Charge for FGB, FGC, FGD, BSA-B, BSA-C, BSA-D and SAC Access Service	135
	(J) Determination of Interstate Charges for Mixed Interstate and Intrastate Switched Access	135
	(K) Local Dial-It Services	135
	(L) Directory Assistance	136
	(M) (Reserved for Future Use)	136
	(N) Description and Application of Rates	136
	(1) Determination of Premium Rates	136
	(2) Switched Transport	137
	(3) Extended FGA and BSA-A Terminating Traffic	140
	(4) Equal Access Notification	141
	(5) End Office Switching	141
	(6) Tandem Switch Signaling (TSS)	141.1
	(7) Dedicated Trunk Port Charge	141.2
	(8) Shared Trunk Port Charge	141.2
	(9) 500 NXX Translation Nonrecurring Charge	142
	(10) Carrier Identification Parameter (CIP)	142
	(O) Measuring Access Minutes	142
	(1) Feature Group A and BSA-A Usage Measurement	143
	(2) Feature Group B and BSA-B Usage Measurement	144
	(3) Usage Measurement Not Available for Feature Groups A and B and BSAs A and B	144
	(4) Feature Group C and BSA-C Usage Measurement	146
	(5) Feature Group D and BSA-D Usage Measurement	147
	(6) SAC Access Service Usage Measurement	148
	(P) FGD and BSA-D Switched Access Service with 950-XXXX Access	148
4.5.3	(Reserved for Future Use)	148
4.5.4	(Reserved for Future Use)	149
4.5.5	Application of Rates for FGA and BSA-A Extension Service	149
4.5.6	(Reserved for Future Use)	149
4.5.7	(Reserved for Future Use)	149
4.5.8	(Reserved for Future Use)	149
4.5.9	Shared Use Analog and Digital High Capacity Services	149
4.5.10	Basic Service Elements (BSEs)	149.1

FACILITIES FOR INTRASTATE ACCESS
SECTION 4 TABLE OF CONTENTS (Cont'd)

4.	<u>SWITCHED ACCESS (Cont'd)</u>	<u>Sheet</u>	
4.6	<u>Rates and Charges</u>	150	
4.6.1	Nonrecurring Charges	150	
	(A) (Reserved for Future Use)	150	
	(B) Switched Access Service Ordering Charges	150	
	(C) Design Change Charge	150	
	(D) (Reserved for Future Use)	150	(C)
	(E) 500 NXX Translation Charge	150	
4.6.2	Switched Transport	151	
	(A) Tandem-Switched Transport-Facility	151	
	(B) Tandem-Switched Transport-Termination	151	
	(C) Tandem Switching	151	
	(D) Shared Multiplexing	151	
	(E) Interconnection Rate	151	
	(F) Direct-Trunked Transport-Voice Grade	151	
	(G) Direct-Trunked Transport-DS1	151	
	(H) Direct-Trunked Transport-DS3	151	
	(I) Dedicated Trunk Port	151.1	
	(J) Entrance Facility-Voice Grade	151.1	
	(K) Entrance Facility-DS1	151.1	
	(L) Entrance Facility-DS3	151.1	
	(M) Multiplexing	151.1	
4.6.3	End Office Services	152	
	(A) 800/888/877 Data Base Query Service	152	
	(B) End Office Switching-Bundled (EOSB)	152	
	(C) End Office Switching-Unbundled (EOSU)-Circuit Switched Line	152	
	(D) End Office Switching-Unbundled (EOSU)-Circuit Switched Trunk	152	
	(E) Alternate Traffic Routing - BSE	152	
	(F) Automatic Number Identification (ANI) - BSE	152.1	
	(G) User Transfer -BSE	152.1	
	(H) Hunt Group Arrangement - BSE	152.1	
	(I) Queuing - BSE	152.1	
	(J) Uniform Call Distribution - BSE	152.1	
	(K) Network Blocking Charge	152.1	(C)
	(L) Remote Call Forwarding - BSE	152.2	
	(M) Direct Inward Dialing (DID) - BSE	152.2	
	(N) Billed Number Screening (BNS) - BSE	152.2	
	(O) Shared Trunk Port	152.2	
	(P) Dedicated Trunk Port	152.2	(N)
4.6.4	(Reserved For Future Use)	153	(C)
4.6.5	FGA and BSA-A Usage Sensitive Credit Allowance	153	
4.6.6	(Reserved For Future Use)		
4.6.7	Assumed Minutes of Use Monthly Surrogate	153	

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS

4.1 General

Switched Access provides two-point communications paths between the point of termination at a CDL and the points of termination at Telephone Company end user premises within the Access Area. Each path is established through the use of Switched Transport, (Entrance Facilities, Direct-Trunked Transport and/or Tandem Switched Transport) End Office Services, and Common Lines or Special Access Lines. Switched Access provides for the ability to originate calls from an end user's premises to the CDL and to terminate calls from the CDL to an end user's premises. Specific descriptions of Switched Access are in 4.2.

Switched Access Service purchased from the provisions of this tariff may be commingled with unbundled network elements, where available, or unbundled network element combinations, where available, purchased pursuant to the Commission's Part 51 Interconnection Rules and in compliance with the Federal Communications Commission's Report and Order on Remand and Further Notice of Proposed Rulemaking in CC Docket Nos. 01-338, 96-98 and 98-147, adopted February 20, 2003 and released August 21, 2003 (FCC 03-36). Unbundled elements and commingling are not available in designated rural CenturyLink Operating Companies where a 251 (f) exemption is in effect.

(C)
|
(C)

Switched Access is ordered in either quantities of lines, trunks or in Busy Hour Minutes of Capacity (BHMC). FGA and BSA-A is furnished on a per-line basis, and FGB, FGC, FGD, BSA-B, BSA-C, BSA-D and SAC Access Service are furnished on a per-trunk basis in accordance with the capacity ordered in trunks or BHMC.

Quantities of lines, trunks or total BHMC of the circuit group connecting the first point of switching and the CDL are determined at the Telephone Company's first point of switching.

A customer may designate one or more CDLs within the LATA for FGA, FGB, FGC, FGD, BSA-A, BSA-B, BSA-C, BSA-D Switched Access or SAC Access Service, except that in the case of 800 SAC Access Service, customers may request connections only to suitably equipped end offices and access tandem offices as discussed in 3.1.1(D).

The following option will not be applicable to FGC, FGD, BSA-C and BSA-D. When the first point of switching and the CDL are in the same Wire Center Area, transport for FGA, FGB, BSA-A or BSA-B Switched Access Service is rated as in Section 4.2.3. When the Telephone Company's first point of switching and the CDL are served by different Wire Center Areas for FGA, FGB, BSA-A or BSA-B Service, but within the same LATA, the customer will be given an option on how the transport will be rated. In this instance, the customer may opt to have the transport rated as Switched Transport from the wire center serving the existing CDL to the end office(s) originating or terminating the traffic, in 4.2.3(A)(1), or choose to have that portion of transport between the wire center serving the existing CDL and the selected first point of switching rated as Special Transport. By selecting the Special Transport option, the customer has established a new CDL for Switched Access rating purposes in the selected Access Area

(M)

(M) Material omitted from this page now appears on Page 70.1

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS

4.1 General (Cont'd)

That Transport between the wire center serving the existing CDL and the new CDL is rated as Special Transport, in 5.1.1(B), and Switched Access rates will be applicable from the wire center serving the new CDL to each end office originating or terminating traffic within the selected FGA, FGB, BSA-A or BSA-B Access Area.

(M)

A Special Access Line charge is also applicable where the customer chooses the Special Transport option as in 5.1.1(C). Switched Transport and Special Transport shall not be combined within the same hunt group arrangement. When the customer requests to change for rating purposes from one type of transport to another (e.g., Special to Switched), the Subsequent Ordering Charge - Switched Access, in 4.6.1(B) or the Subsequent Ordering Charge - Special Access in 5.6.1(D)(1) (b) will apply. The charge for the change depends on the type of transport option being selected by the customer.

When Switched Access is ordered in BHMC, the BHMC must be differentiated by Feature Group type and directionality of traffic as in 4.3.2 in order for the Telephone Company to properly design Switched Access to meet the traffic carrying capacity requirements of the customer.

When a customer plans to use Switched Access in connection with the resale of services of an IC, the provisions for such Switched Access charges are in Section 12.

(M)

Switched Access is provided with basic testing as described in 4.2.1, 4.2.2, and 4.2.7. Additional testing is provided as described in 6.6. Testing is provided only on the FIA supplied by the Telephone Company.

(N)

Switched Access Service purchased from the provisions of this tariff may be commingled with unbundled network elements, where available, or unbundled network element combinations, where available, purchased pursuant to the Commission's Part 51 Interconnection Rules and in compliance with the Federal Communications Commission's Report and Order and Order on Remand and Further Notice of Proposed Rulemaking in CC Docket Nos. 01-338, 96-98 and 98-147, adopted February 20, 2003 and released August 21, 2003 (FCC 03-36). Unbundled elements and commingling are not available in designated rural CenturyLink Operating Companies where a 251 (f) exemption is in effect.

A customer may designate one or more CDLs within the LATA for FGA, FGB, FGC, FGD, BSA-A, BSA-B, BSA-C, BSA-D Switched Access or SAC Access Service.

(N)

(M) This material previously appeared on Page 70.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.1 Descriptions of Feature Groups (Cont'd)

(C) Feature Group C

Feature Group C (FGC) provides trunk-side access to Telephone Company end office switches for providers of MTS and WATS for originating and terminating communications. FGC is available in all end offices which are not equipped for FGD or BSA-D End Office Services.

(C)
|
(C)

- (1) FGC is provided at all Telephone Company end office switches or Telephone Company designated access tandem switches. FGC is available at an end office switch unless FGD or BSA-D is provided in the same office. When FGD or BSA-D is available, FGC will be discontinued for Interexchange Carriers (ICs) as soon as the conversion to FGD or BSA-D can be arranged.

FGC utilizes a two-point electrical communications path between the Interface Arrangement and Common Line or Special Access Line which is a voice grade transmission path comprised of any form or configuration of plant capable of, and typically used in the telecommunications industry for, the transmission of the human voice and associated signals within the frequency bandwidth of approximately 300 to 3000 Hz.

- (2) FGC is provided as trunk-side switching through the use of end office switch trunk equipment. The switch trunk equipment is provided with answer and disconnect supervisory signaling. Wink start pulsing signals are provided in all offices where available. In those offices where wink start pulsing signals are not available, delay dial start pulsing signals will be provided.
- (3) The Telephone Company will select the trunking arrangement from the end office within the selected Access Area from which FGC is to be provided. If the customer orders an ANI arrangement or Service Class Routing Arrangement, special routing and trunking arrangements may be required.

(M)
|
(M)

(M) Material omitted from this page now appears on Page 82.1.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.1 Descriptions of Feature Groups (Cont'd)

(C) Feature Group C (Cont'd)

- (4) FGC is arranged for either originating calling only, terminating calling only, or two-way calling based on the trunks or BHMC ordered. The Telephone Company will determine the type of Directional calling to be provided unless the customer requests the option, Customer Specification of Directionality as described in 4.2.5(H). For such specification, additional charges on an Individual Case Basis will apply if the trunk group Routing arrangements are different from that the Telephone Company would have provided without such special arrangements. Originating calling permits the origination of calls from the end user to the CDL. Terminating calling permits the termination of calls from the CDL to the end user. Two-way calling permits either the origination or termination of calls, but not simultaneously.

(M)

(M)

(M)) This material previously appeared on Page 82.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.1 Descriptions of Feature Groups (Cont'd)

(C) Feature Group C (Cont'd)

(14) FGC may, at the option of the customer, be provided with Alternate Traffic Routing. This arrangement, as shown in 4.2.5(A), delivers originating traffic from an end office over a designated trunk group to the CDL. When that trunk group is fully loaded, additional originating traffic is automatically delivered over one or more designated trunk groups to one or more CDLs.

(15) FGC may, at the option of the customer, be provided with a Service Class Routing Arrangement. This arrangement allows originating traffic to be delivered over selected trunk groups to specified CDL based on service prefix (e.g., 0-, 0+, 1+, 01, 011); service class codes (e.g., 500, 700, TFC, 900); or end user originating line class of service (e.g., coin, multiparty, hotel/motel).

(C)

(16) (Reserved for Future Use)

(17) FGC may, at the option of the customer, be provided with a Trunk Access Limitation Arrangement in all Telephone Company end offices. This arrangement provides for the routing of designated (e.g., 900 Service Code) originating calls to a specified number of transmission paths in a trunk group to the CDL in order to limit the amount of such traffic that can be completed.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.1 Descriptions of Feature Groups (Cont'd)

(D) Feature Group D (Cont'd)

- (9) FGD may, at the option of the customer, be arranged to provide ANI arrangement to obtain the calling station billing number. The ANI arrangement provides ten digit station billing number information to the CDL. When SS7 Out of Band Signaling is specified, the customer may obtain an ANI equivalent by ordering the Charge Number optional feature as described in 4.2.5(A)(D). In those situations where no billing number is available in the end office switch, as with 4/8 party service, no ten digit number will be provided, only the area code and an "operator identification" information digit will be provided.

In those cases where an ANI failure has occurred in the end office switch, no ten digit number will be provided, and an "identification failure" information digit will be provided. ANI will be made available using multifrequency signaling provided by the Telephone Company.

Dependent upon the group type, the ANI spill may be forwarded prior to the called number in appropriately equipped end offices. When the ANI spill is sent prior to the called number, ten digits will be forwarded (NPA + NXX-XXXX). When the ANI spill is sent after the called number, the conventional seven digits will be forwarded. The Telephone Company will determine the sequencing and protocol of the ANI spill and called number.

- (10) FGD may, at the option of the customer, be arranged for the International Direct Distance Dialing (IDDD) Arrangement in the originating direction. End offices or Telephone Company access tandem switches which are equipped for IDDD will be designated by the Telephone Company. The CDL must be equipped to receive the IDDD supervisory and address signals and the CDL must provide operator assistance to the end users if necessary to obtain the IDDD address signals once the CDL acknowledges it is ready to receive IDDD address signals.

FGD may also be arranged to forward the international calls of one or more international carriers to the customer. This arrangement requires verification by the Telephone Company that the customer is authorized to forward such calls.

- (11) FGD is provided with basic testing at no additional charge. Basic tests include: loss, 3 tone slope, (C-message and C-notched), and where applicable, signaling and balance testing.

(N)
|
(N)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.1 Descriptions of Feature Groups (Cont'd)

(D) Feature Group D (Cont'd)

(11) (Cont'd)

(N)

- (a) Where Telephone Company equipment is available, a seven digit access number will be provided to the customer for testing in the terminating direction. These access numbers shall include: balance (100 type) test line, milliwatt (102 type) test line, nonsynchronous or synchronous test line, automatic transmission measuring (105 type) test line, data transmission (107 type) test line, loop around test line, short circuit test line and open circuit test line. Access to test lines by other than seven digits is at the option of the Telephone Company and may vary in availability.
- (b) Where Telephone Company equipment is available and the customer is equipped with compatible equipment (remote office test lines and 105 test lines with associated responders or their functional equivalent), FGD will be provided with automatic testing.
- (c) At the option of the Telephone Company, cooperative testing may be provided in lieu of automatic testing. Cooperative testing is where the Telephone Company provides a technician at its office(s) and the customer provides a technician at its CDL, with suitable test equipment to perform the required tests. The Telephone Company will routinely perform maintenance testing from its access tandem or end office (if direct routed) to the customer's first point of switching. Additional testing charges will apply as in 6.6 when: (a) the customer requests a test not specified in the preceding; (b) the test requested is not essential to the ongoing maintenance of FGD; or (c) the customer requests testing on a more frequent basis than scheduled in the Telephone Company's Central Office Maintenance Planning System (COMPS).

(N)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.1 Descriptions of Feature Groups (Cont'd)

(D) Feature Group D (Cont'd)

(11) (Cont'd)

(N)

(d) When FGD, TFC SAC Access service with SS7 Out of Band Signaling is ordered, network compatibility and other operational tests will be performed cooperatively by the Telephone Company and the customer at locations, dates, and times as specified by the Telephone Company in consultation with the customer. These tests are as specified in Bellcore Technical Reference Publication TR-TSV-000905. Successful completion is necessary to receive the SS7 signaling option. To protect the security of the SS7 network, certain of the information provided, i.e., point codes, by the Telephone Company to the customer will be subject to a nondisclosure agreement.

(12) FGD may, at the option of the customer, be provided with Alternate Traffic Routing. This arrangement, as shown in 4.2.5(A), delivers originating traffic from an end office over a designated trunk group to the CDL. When that trunk group is fully loaded, additional originating traffic is automatically delivered over one or more designated trunk groups to one or more CDLs.

(N)

(13) FGD is provided with basic testing at no additional charge. Basic tests include: loss, 3 tone slope, (C-message and C-notched), and where applicable, signaling and balance testing.

(M)

(a) Where Telephone Company equipment is available, a seven digit access number will be provided to the customer for testing in the terminating direction. These access numbers shall include: balance (100 type) test line, milliwatt (102 type) test line, nonsynchronous or synchronous test line, automatic transmission measuring (105 type) test line, data transmission (107 type) test line, loop around test line, short circuit test line and open circuit test line. Access to test lines by other than seven digits is at the option of the Telephone Company and may vary in availability.

(M)

(M) This material previously appeared on Sheet 93.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.1 Descriptions of Feature Groups (Cont'd)

(D) Feature Group D (Cont'd)

(13) (Cont'd)

(M)

(M)

(b) Where Telephone Company equipment is available and the customer is equipped with compatible equipment (remote office test lines and 105 test lines with associated responders or their functional equivalent), FGD will be provided with automatic testing.

(c) At the option of the Telephone Company, cooperative testing may be provided in lieu of automatic testing. Cooperative testing is where the Telephone Company provides a technician at its office(s) and the customer provides a technician at its CDL, with suitable test equipment to perform the required tests. The Telephone Company will routinely perform maintenance testing from its access tandem or end office (if direct routed) to the customer's first point of switching. Additional testing charges will apply as in 6.6 when: (a) the customer requests a test not specified in the preceding; (b) the test requested is not essential to the ongoing maintenance of FGD; or (c) the customer requests testing on a more frequent basis than scheduled in the Telephone Company's Central Office Maintenance Planning System (COMPS).

(d) When FGD or TFC SAC Access service with SS7 Out of Band Signaling is ordered, network compatibility and other operational tests will be performed cooperatively by the Telephone Company and the customer at locations, dates, and times as specified by the Telephone Company in consultation with the customer. These tests are as specified in Bellcore Technical Reference Publication TR-TSV-000905. Successful completion is necessary to receive the SS7 signaling option. To protect the security of the SS7 network, certain of the information provided, i.e., point codes, by the Telephone Company to the customer will be subject to a nondisclosure agreement.

(T)

(M) Material omitted from this page now appears on Sheet 92.2.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.1 Descriptions of Feature Groups (Cont'd)

(D) Feature Group D (Cont'd)

- (14) FGD may, at the option of the customer, be provided with Alternate Traffic Routing. This arrangement, as shown in 4.2.5(A), delivers originating traffic from an end office over a designated trunk group to the CDL. When that trunk group is fully loaded, additional originating traffic is automatically delivered over one or more designated trunk groups to one or more CDLs.
- (15) FGD may, at the option of the customer, be provided with a Service Class Routing Arrangement. This arrangement allows originating traffic to be delivered over selected trunk groups to specified CDLs based on service prefix code (e.g., 0-, 0+, 1+, 01, 011); service class codes (e.g., 500, 700, TFC, 900); or end user originating line class of service (e.g., coin, multiparty, hotel/motel). Service classes of traffic unable to be served by a customer will be handled at the option of the Telephone Company. (T)
- (16) (Reserved for Future Use)
- (17) FGD will be arranged to accept calls from Telephone Company local service without the 101XXXX uniform access code. Each Telephone Company local service will be marked to identify which 101XXXX code its calls will be directed to for InterLATA Area service.
- (18) FGD may, at the option of the customer, be provided with a Trunk Access Limitation Arrangement. The Trunk Access Limitation Arrangement provides for the routing of designated (e.g., 900 Service class code) originating calls to a specified number of transmission paths in a trunk group.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.2 Description of Basic Serving Arrangements (BSAs) (Cont'd)

(D) BSA-D (Cont'd)

- (12) BSA-D may, at the option of the customer, be provided with Alternate Traffic Routing. This arrangement, as shown in 4.2.22, delivers originating traffic from an end office over a designated trunk group to the CDL. When that trunk group is fully loaded, additional originating traffic is automatically delivered over one or more designated trunk groups to one or more CDLs.
- (13) BSA-D may, at the option of the customer, be provided with a Service Class Routing Arrangement. This arrangement allows originating traffic to be delivered over selected trunk groups to specified CDLs based on service prefix code (e.g., 0-, 0+, 1+, 01, 011); service class codes (e.g., 500, 700, TFC, 900); or end user originating line class of service (e.g., coin, multiparty, hotel/motel). Service classes of traffic unable to be served by a customer will be handled at the option of the Telephone Company. (T)
- (14) BSA-D will be arranged to accept calls from Telephone Company local service without the 101XXXX uniform access code. Each Telephone Company local service will be marked to identify which 101XXXX code its calls will be directed to for InterLATA Area service.
- (15) BSA-D may, at the option of the customer, be provided with a Trunk Access Limitation Arrangement. The Trunk Access Limitation Arrangement provides for the routing of designated (e.g., 900 Service class code) originating calls to a specified number of transmission paths in a trunk group.
- (16) BSA-D may, at the option of the customer, be provided with an Operator Assistance Full Feature Arrangement. This arrangement provides, to the customer operator, the initial coin control function. BSA-D is provided in a directly routed arrangement from the end office switch when this feature is provided. This feature may require the routing by Service Class Routing Arrangement. The coin collection and return protocol required by the customer must be compatible with Telephone Company equipment. Offering of this feature is contingent upon suitable administrative procedures/agreements for coin services being negotiated between the customer and the Telephone Company. This option is unavailable in conjunction with SS7 Out of Band Signaling. (N)
- (17) BSA-D is provided with either Type A, Type B, or Type C transmission performance as follows: a) when routed directly to the end office, either Type B or Type C is provided; b) when routed to a Telephone Company access tandem, only Type A is provided; c) Type A is provided on the transmission path from the Telephone Company access tandem to the end office. Type C transmission performance is provided with Interface Arrangement 1. Type A and Type B are provided with Interface Arrangements 2 through 10. In addition, Data Transmission Parameters may, at the option of the customer, be provided with BSA-D.
- (18) BSA-D trunking arrangements are available with two basic forms of signaling protocol. The standard signaling protocol provided with BSA-D is Overlap Outpulsing. At the option of the customer, where technically available BSA-D may be provided with Non-Overlap Outpulsing signaling protocol. (N)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.3 Description of Switched Transport

(A) General

(1) (Cont'd)

The Interconnection Rate is assessed upon all customers for interconnecting with the Telephone Company's switched access network. The Interconnection Rate is further described in 4.2.3(E).

The Dedicated Switched Access Transport Rate is assessed upon customers subscribing to CCS7 Access Service for the use of facilities between the customer's common channel signaling network and the Telephone Company's signaling transfer point. It is a flat rated, distance-sensitive monthly rate. This rate element is further described in 4.2.3(A)(2).

The application of the Switched Transport rates and the determination of the mileage measurement for Switched Transport Facility is in 4.5.2(N)(2).

- (2) Switched Transport is a two-way voice frequency transmission path composed of facilities determined by the Telephone Company. The two-way voice frequency path permits the transport of calls in the originating direction (from the end office switch to the CDL), and in the terminating direction (from the CDL to the end office switch), but not simultaneously. The voice frequency transmission path may be comprised of any form or configuration of plant capable of and typically used in the telecommunications industry for the transmission of the human voice and associated telephone signals within the frequency bandwidth of approximately 300 to 3000 Hz. Direct-Trunked Transport and Entrance Facilities are composed of facilities as ordered by the customer.

Switched Transport facilities will be engineered and routed based on standard engineering methods, available facilities and equipment, Telephone Company traffic routing plans and the customer's order for service.

(N)
|
(N)

The Telephone Company will work cooperatively with the customer in determining (1) whether the first point of switching will be an end office switch or an access tandem switch, and (2) the directionality of the service.

- (3) For Tandem-Switched Transport the number of Switched Transport transmission paths provided between an end office switch and a Telephone Company access tandem are determined by the Telephone Company using standard traffic engineering methods. The number of Switched Transport transmission paths provided between the Telephone Company access tandem and serving wire center of the CDL is determined by the customer's order. If ordered in BHMC, the Telephone Company will determine the number of trunks, using standard traffic engineering methods. When Direct-Trunked Transport is ordered directly to a Telephone Company access tandem, facilities between the serving wire center of the CDL and the Telephone Company access tandem will be determined by the customer's order.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.3 Description of Switched Transport (Cont'd)

(A) General (Cont'd)

(4) The number of Switched Transport transmission paths provided between an end office switch and the first point of switching are determined by the Telephone Company using standard traffic engineering methods. The number of Switched Transport transmission paths provided between the first point of switching and the CDL is determined:

(a) by the customer, when ordering FGA or BSA-A, based on the number of lines ordered, or;

(b) by the Telephone Company, when the customer orders FGB, FGC, FGD, BSA-B, BSA-C, BSA-D or SAC Access Service. If ordered in trunks, the customer may determine the number of trunks. If ordered in BHMC, the Telephone Company will determine the number of trunks, using standard traffic engineering methods.

(B) Entrance Facility

The Entrance Facility provides the transmission path and interface between the Telephone Company provided Switched Access and customer provided facilities at the point of termination at the CDL.

Switched Access is provided in a number of separate Entrance Facilities. Each Entrance Facility provides a specified facility interface (e.g., two-wire, four-wire, DS1, etc.). Each High Capacity Analog or Digital Entrance Facility, as listed following, is subject to the minimum capacity requirements when ordered as in 3.5.5. Provision of the Entrance Facilities for two-wire and four-wire voice frequency Entrance Facility and any Optional Arrangements may require placement of Telephone Company equipment [e.g., supervisory signaling equipment as described in 4.2.3(G)(4)] on the customer's premises.

Where transmission facilities permit, the individual transmission paths between the point of termination and the first point of switching may, at the option of the customer, be provided with Optional Arrangements as in (C).

The following Standard Entrance Facilities are available:

Two-Wire VF

Four-Wire VF

Group Analog (12/30/93 existing customers only)

Supergroup Analog (12/30/93 existing customers only)

Mastergroup Analog (12/30/93 existing customers only)

DS1 Digital

DS1C Digital (12/30/93 existing customers only)

DS3 Digital

DS3C Digital (12/30/93 existing customers only)

(C)

|

(C)

(C)

(C)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.3 Description of Switched Transport (Cont'd)

(B) Entrance Facility(Cont'd)

(2) Four-Wire Voice Frequency Entrance Facility (Cont'd)

- (b) The transmission path between the point of termination at the CDL and the first point of switching may be comprised of any form or configuration of plant capable of and typically used in the telecommunications industry for the transmission of the human voice and associated telephone signals within the frequency bandwidth of 300 to 3000 Hz.
- (c) The Entrance Facility is provided with loop supervisory signaling. When the Entrance Facility is associated with FGA or BSA-A, such signaling may be loop start or ground start signaling. When the Entrance Facility is associated with FGB, FGC, FGD, BSA-B, BSA-C and BSA-D such signaling, except for two-way calling, may be reverse battery signaling. The Entrance Facility may, at the option of the customer, be provided with supervisory signaling as in 4.2.3 (G)(4).

(3) Group Analog Entrance Facility (12/30/93 Existing Customers Only)

(C)

- (a) The Group Analog Entrance Facility provides a group level analog transmission at the point of termination at the CDL subject to the limitations in 3.5. The Entrance Facility is capable of transmitting electrical signals between the frequencies of 60 to 108 kHz, with the capability to multiplex up to 12 voice frequency transmission paths.

Between the serving wire center and the point of termination at the CDL, the Telephone Company may, at its option, provide multiplex equipment to derive 12 transmission paths of frequency bandwidth of approximately 300 to 3000 Hz.

- (b) The Entrance Facility is provided with individual transmission path supervisory signaling.
- (c) The Group Analog Entrance Facility is obsolete technology and is available only to existing customers as of December 30, 1993.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.3 Description of Switched Transport (Cont'd)

(B) Entrance Facility (Cont'd)

(4) Supergroup Analog Entrance Facility (12/30/93 Existing Customers Only) (C)

- (a) The Supergroup Entrance Facility Arrangement provides supergroup level analog transmission at the point of termination at the CDL subject to the limitations in 3.5. The Entrance Facility is capable of transmitting electrical signals between the frequencies of 312 to 552 kHz, with the capability to multiplex up to 60 voice frequency transmission paths.

Between the first point of switching and the point of termination the Telephone Company may, at its option, provide multiplex equipment to derive 60 transmission paths of frequency bandwidth of approximately 300 to 3000 Hz to promote transmission efficiency, if required.

- (b) The Entrance Facility provided with individual transmission path SF supervisory signaling.
- (c) The Supergroup Analog Entrance Facility is obsolete technology and is available only to existing customers as of December 30, 1993.

(5) Mastergroup Analog Entrance Facility (12/30/93 Existing Customers Only) (C)

- (a) The Mastergroup Analog Entrance Facility provides mastergroup level analog transmission at the point of termination at the CDL subject to the limitations in 3.5. The Entrance Facility is capable of transmitting electrical signals between the frequencies of 564 to 3084 kHz, with the capability to multiplex up to 600 voice frequency transmission paths.

Between the first point of switching and the point of termination at the CDL, the Telephone Company may, at its option, provide multiplex equipment to derive 600 transmission paths of frequency bandwidth of approximately 300 to 3000 Hz to promote transmission efficiency, if required.

- (b) The Entrance Facility is provided with individual transmission path SF supervisory signaling.
- (c) The Mastergroup Analog Entrance Facility is obsolete technology and is available only to existing customers as of December 30, 1993.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.3 Description of Switched Transport (Cont'd)

(B) Interface Arrangements (Cont'd)

(6) DS1 Digital Entrance Facility

- (a) The DS1 Digital Entrance Facility provides DS1 level digital transmission at the point of termination at the CDL subject to the limitations in 3.5. The Entrance Facility is capable of transmitting electrical signals at 1.544 Mbps, with the capability to multiplex up to 24 voice frequency transmission paths.

Between the first point of switching and the point of termination at the CDL, when analog switching utilizing analog terminations is provided, the Telephone Company may, at its option, provide multiplex equipment to derive 24 transmission paths of frequency bandwidth of approximately 300 to 3000 Hz. When digital switching or analog switching with digital carrier terminations is provided, the Telephone Company will provide, at the first point of switching, DS1 signals in D4 or D3 format.

- (b) The Entrance Facility is provided with individual transmission path bit stream supervisory signaling.

(7) DS1C Digital Entrance Facility (12/30/93 Existing Customers Only)

(C)

- (a) The DS1C Digital Entrance Facility provides a DS1C level digital transmission at the point of termination at the CDL subject to the limitations in 3.5. The Entrance Facility is capable of transmitting electrical signals at 3.152 Mbps, with the capability to multiplex up to 48 voice frequency transmission paths.

Between the first point of switching and the point of termination, when analog switching utilizing analog terminations is provided, the Telephone Company may, at its option, provide multiplex equipment to derive up to 48 voice frequency transmission paths of frequency bandwidth of approximately 300 to 3000 Hz. When digital switching or analog switching with digital carrier terminations is provided, the Telephone Company will provide, at the first point of switching, DS1 signals in D4 or D3 format.

- (b) The Entrance Facility is provided with individual transmission path bit stream supervisory signaling.

- (c) As of December 30, 1993, the DS1C Digital Entrance Facility is available to existing customers only.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.3 Description of Switched Transport (Cont'd)

(E) Interconnection Rate

The Interconnection Rate is assessed upon all customers for interconnecting with the Telephone Company's switched access network. The Interconnection Rate has two rate levels. One rate applies to customers utilizing Telephone Company transport and a different rate that is applicable to Switched Access EIS Cross Connect arrangements. It is a usage rated per minute rate and applies to all originating and terminating minutes of use whether transported via Direct-Trunked Transport, Tandem-Switched Transport, or Entrance Facilities arrangements. The Interconnection Rate does not apply to switched access minutes of use that originate or terminate at MTSOs directly interconnected to a Telephone Company access tandem office.

The application of originating and terminating rates are as set forth below:

(a) Terminating per minute charge(s) apply to:

- all terminating access minutes of use;
- all originating access minutes of use associated with FGA or BSA-A Access Services where the off-hook supervisory signaling is forwarded by the customer's equipment when the called party answers;
- all originating access minutes of use associated with calls placed to Service Access Code numbers, less those originating access minutes of use associated with calls placed to 500, 700, TFC and 900 numbers for which the customer furnishes a report as described in Section 12, of either the number of minutes or a report of the percent of minutes that terminate to a subscriber or common line, rather than a dedicated access line. (T)

(b) The originating per minute charge(s) apply to:

- all originating access minutes of use;
- less those originating access minutes of use associated with FGA or BSA-A Access Services where the off-hook supervisory signaling is forwarded by the customer's equipment when the called party answers;
- less all originating access minutes of use associated with calls placed to Service Access Code numbers;
- plus all originating access minutes of use associated with calls placed to 500, 700, TFC and 900 numbers for which the customer furnishes a report of either the number of minutes or a report of the percent of minutes that terminate to a subscriber or common line, and for which a corresponding reduction in the number of terminating access minutes of use has been made as set forth in (a). (T)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.5 End Office Services Optional Arrangements (Cont'd)

(B) Automatic Number Identification (ANI) Arrangement (Cont'd)

- (1) Telephone number is the station billing number - no special treatment is required. (M)
- (2) Multiparty line telephone number is a 2 (in some instances), 4, or 8 party line and cannot be identified - number must be obtained via an operator or in some other manner.
- (3) ANI failure has occurred in the end office switch which prevents identification of calling telephone number - number must be obtained by operator or in some other manner.
- (4) (Reserved for Future Use)
- (5) The configuration of the line requires special screening or handling by the customer, or
- (6) Call is an Automatic Identified Outward Dialed (AIOD) call from end user terminal equipment.

These ANI information digits are available with FGB, FGC, and FGD only. In addition, the following information digits are available with FGD only:

- InterLATA Area restricted - telephone number is identified line.
- InterLATA Area restricted - line requires special screening or handling by the customer.

These information digits will be transmitted as agreed to by the customer and the Telephone Company.

The ANI Arrangement is available with BSA-B, BSA-C and BSA-D as a chargeable BSE as specified in 4.2.22 and 4.5.10.

(C) Intra Access Area Call Denial on Line or Hunt Group

This option is provided in conjunction with FGA and BSA-A and allows for the screening of terminating calls within the FGA and BSA-A Access Area, and for completion only of calls to 411, 611, 911, 800, 888, 877, 555-1212, and a specified set of NXX codes within the FGA and BSA-A Access Area. The set of NXX codes to which calls will be completed is selected by the FGA or BSA-A customer, in cooperation with the Telephone Company, from those NXX codes within the local calling area of the end office where the FGA or BSA-A connection is provided. All other calls are routed to a reorder tone or recorded announcement. This arrangement is provided at no charge in Telephone Company end offices, where available.

(M) This material previously appeared on Sheet 105.1.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.5 End Office Services Optional Arrangements (Cont'd)

(V) Switched Access Interface (Cont'd)

- (4) The following matrix details the direction, call type, service prefix and traffic types provided on each Switched Access Interface Arrangement.

	<u>Switched Access Interface Arrangements</u>			(T)
	<u>Unrestricted Arrangement</u>	<u>TFC Type Terminating Only</u>	<u>Combined Originating/TFC Type Terminating</u>	
Section Ref.	(V)(1)(a)	(V)(2)	(V)(3)	
<u>Directionality</u>				
Originating Only	x			
Terminating Only		x		
Two-Way			x	
<u>Call Type (1+)</u>				
Local	B	B	B	
IntraLATA/Intrast.	R/D	C	R/D/C	
InterLATA/Intrast.	D	C	D/C	
<u>Service Prefix</u>				
0-	R		R	
00-	D		D	
0+	D		D	
IDDD	D		D	
101XXXX	D/B		D/B	
<u>Traffic Type</u>				
411	B		B	
911	R		R	
976	R		R	
700	D		D	
500/800/888/877/900	D		D	

D = Telephone Company DELIVERS traffic to the customer.
R = Telephone Company RETAINS and completes traffic.
C = Telephone Company COMPLETES traffic to the end user's premises.
B = Telephone Company BLOCKS traffic to an announcement.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.5 End Office Services Optional Arrangements (Cont'd)

(Z) (Reserved for Future Use)

(AA) Signaling System 7 (SS7) Out of Band Signaling

(T)

This option is provided in conjunction with Common Channel Signaling System 7 (CCS7) Access Service and is only available with Switched Access FGD or BSA-D service, 500 SAC Access, 800/888/877 SAC Access and 900 SAC Access Services. SS7 Out of Band Signaling provides common channel out of band transmission of address and supervisory SS7 protocol signaling information between the end office or access tandem switching systems and the CDL. FGD or BSA-D Switched Access, 500 SAC Access, 800/888/877 SAC Access and 900 SAC Access service, equipped with SS7 Out of Band Signaling, are available with the following interface arrangements: DS1 Digital, DS1C Digital, DSC Digital, and DS3C Digital. SS7 Out of Band Signaling is provided at suitably equipped Telephone Company end office or access tandem switches. The technical specifications for SS7 Out of Band Signaling are described in Bellcore Technical Reference Publication TR-TSV-000905.

(AB) Calling Party Number (CPN) Parameter

(T)

The CPN parameter, available as a nonchargeable option for originating FGD or BSA-D with SS7 Out of Band Signaling, provides for the automatic transmission of the ten digit directory number, associated with a calling station, to the customer's premises for originating calls. The ten digit number consists of the NPA plus the seven digit telephone number which may or may not be the same number as the calling station's charge number. The CPN parameter also includes a "privacy indicator" which allows the ten digit telephone number to be coded as presented or restricted for delivery to the called end user. The technical specifications for CPN are described in Bellcore Technical Reference Publication TR-TSV-000905.

These information digits shall only be used for billing and collection, routing, screening, and completion of the originating subscriber's call or transaction or for service directly related to the originating subscriber's call or transaction.

(N)

The information provided shall not be reused or resold without first notifying the originating telephone subscriber and obtaining affirmative consent of the subscriber for reuse or resale.

Unless the originating subscriber has given consent for the reuse or resale, any information provided shall not be used for any purpose other than:

performing the services or transactions that are subject of the originating subscriber's call; ensuring network performance security, and the effectiveness of call delivery; compiling, using and disclosing aggregate information, and, complying with applicable laws.

The above restrictions shall not prevent the subscriber to the CN Parameter from using information acquired from a CN Parameter, such as the telephone number or information derived from analysis of the characteristics of calls received through the CN Parameter, to offer a product or service that is directly related to the products or services previously purchased by a customer of the CN Parameter subscriber.

(N)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.5 End Office Services Optional Arrangements (Cont'd)

(AC) Carrier Selection Parameter (CSP) (T)

The CSP, available as a nonchargeable option for originating FGD or originating BSA-D with SS7 Out of Band Signaling, provides for the automatic transmission of a signaling indicator which signifies to the customer whether or not a given call originated from a presubscribed line. If the line was presubscribed, the indicator will signify if the end user did or did not dial 101XXXX. The technical specifications for CSP are described in Bellcore Technical Reference Publication TR-TSV-000905.

(AD) Charge Number (CN) Parameter (T)

The CN parameter, available as a nonchargeable option for originating FGD with SS7 Out of Band Signaling, is equivalent to the existing ten digit Automatic Number Identification (ANI) available with FGD with MF signaling. When BSA-D with SS7 Out of Band Signaling is specified, the customer may order the CN parameter at the rates for ANI-BSE as shown in 4.6. The CN parameter provides for the automatic transmission of the ten digit billing number of the calling station and the originating line information. The technical specifications for CN are described in Bellcore Technical Reference Publication TR-TSV-000905.

(AE) Tandem Switch Signaling (T)

This option allows for the passing of the Carrier Identification Code (CIC) and the OZZ code or circuit code information needed to perform tandem switching functions. The CIC identifies the uniform access code associated with the Switched Access usage for a specific interexchange carrier. The OZZ code identifies the service class routing code of a multifrequency call that indicates the interexchange carrier's trunk group to which the traffic will be routed. The circuit code identifies the service class routing of an SS7 call that indicates the interexchange carrier's trunk group to which the traffic will be routed (e.g., 0+, 0-, 500, 900, etc). This option is only available with FGD Switched Access, 500 SAC Access, and 900 SAC Access services and can only be provided from equal access end offices. This option is not available from end offices that use alternate technologies to provide equal access capabilities, or from Telephone Company access tandems.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.5 End Office Services Optional Arrangements (Cont'd)

(AF) Tandem Access Sectorization

(T)

(1) Tandem Access Sectorization (TAS) is available to FGD and BSA-D customers with originating traffic routed through an appropriately equipped Telephone Company equal access tandem. TAS provides the customer a method of directing originating FGD and BSA-D traffic, on the basis of all originating end offices in an exchange to a maximum of four (4) different CDLs via the Telephone Company equal access tandem.

(2) For those Telephone Company equal access tandems where TAS is provided, the Telephone Company has subdivided the subtending exchanges into geographical regions (a maximum of 4 per equal access tandem) referred to as Tandem Access Sectorization Regions (TASR). Each TASR is treated as a unit and cannot be subdivided.

The available TASRs are the same for all customers ordering TAS. A customer with multiple CDLs within a LATA can designate the CDL to which all traffic originating from a specific TASR will be routed. A customer may have a maximum of one CDL per TASR. Traffic originating from different TASRs may be routed to the same or different CDL provided that traffic originating from a single TASR may not be routed to more than one CDL.

(3) TAS is available in conjunction with FGD and BSA-D at rates and charges in 4.5.2(N)(6) in addition to switched access charges applicable to FGD and BSA-D usage throughout Section 4.5.

(AG) Carrier Identification Parameter (CIP)

(T)

Carrier Identification Parameter is available as an optional feature in conjunction with originating FGD with SS7 Out of Band Signaling. CIP provides for the transmission of the Carrier Identification Code (CIC) or the access 101XXXX to the customer with the Initial Address Message (IAM). CIP is available with originating FGD in suitably equipped end offices and access tandems. CIP will be populated by a 4-digit CIC at the rates shown in 4.6.8. Application of the charges is in 4.5.2(N)(10).

The Telephone Company will make every effort to maintain the CIP information, equipment and facilities in a format which facilitates the customer's use of the CIP offering. Changes (i.e., technology, customer account makeup, etc.) can occur affecting such information, however, and the Telephone Company cannot guarantee that the CIP equipment and facilities will be completely capable of processing CIP data at all times. Accordingly, the Telephone Company shall not be liable for any incidental, indirect, special or consequential damages (including lost revenue or profits) of any kind, resulting from inaccuracy of CIP data and/or the inability of its equipment and facilities to process CIP data.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.10 (Reserved for Future Use)

4.2.11 TFC Customer Identification Function

(T)

This function utilizes TFC Data Base Query Service, as described in 4.2.19, to screen all ten digits of all TFC type calls generated by end users to determine the customer to which the TFC call is to be routed. This function is provided in conjunction with TFC SAC Access Service. This function is not available with Tandem Switch Signaling.

(T)

(T)

(T)(N)

4.2.12 900 Customer Identification Function

This function provides for screening of the first six digits of all 900-NXX-XXXX type calls generated by end users to determine the customer to which the call is to be routed. This function is provided in conjunction with 900 SAC Access Service and with FGC, FGD, BSA-C and BSA-D. This function is available with Tandem Switch Signaling.

(N)

4.2.13 Design and Routing of Switched Access

The Telephone Company shall work cooperatively with the customer to design and determine the routing of Switched Access including the selection of facilities from the first point of switching to the CDL. The Telephone Company shall also decide if capacity is to be provided by originating only, terminating only or two-way facilities unless the customer requests Customer Specification of Switched Access Directionality for the ordered capacity. Selection of facilities, equipment and routing of the Switched Access is based on standard engineering methods, facilities and equipment available, the Telephone Company traffic routing plans and the customer's order for service.

(N)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.14 Provision of Switched Access Performance Data

Performance data for Switched Access will be made available to the customer based on Telephone Company established intervals and availability. This data may include, but is not limited to, equipment blockage and failure results, ineffective attempt performance, transmission failures, and other service-related data. Any request for data or format that is not Telephone Company Standard will be handled on an Individual Case Basis with any associated cost to be borne by the customer. Performance data related to customer provided facilities will not be provided.

(N)

4.2.15 Transmission Performance

Each Switched Access transmission path is provided with a standard transmission performance. The standard for a particular path is dependent on the Interface Arrangement and whether the Switched Access is routed direct or via an access tandem. In addition, Data Transmission Parameters may be ordered by the customer. The transmission performance parameters are set forth in Section 7000 of the GTE Technical Interface Reference Manual. The transmission performance parameters relate only to the Telephone Company provided portion of the service.

(N)

(N)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.2 Description of Switched Access (Cont'd)

4.2.19 TFC Data Base Query Service

(T)

TFC Data Base Query Service, offered in conjunction with TFC SAC Access Service, performs the TFC Customer Identification Function, as described in 4.2.11, to determine the customer to whom TFC calls must be routed. For all TFC calls originated by an end user, the Telephone Company will perform the customer identification function using a Telephone Company TFC Data Base to screen the dialed ten digits of the TFC call to determine the customer selected by the TFC subscriber to carry that TFC call. If the TFC call originates from an end office switch not equipped to provide the customer identification function, the call will be routed to an access tandem switch equipped to provide the customer identification function. Once customer identification has been established through TFC Data Base Query Service, the TFC call will be routed to the selected customer for completion.

(T)

(T)

(T)

Basic TFC Data Base Queries provide instructions to route TFC calls on a simple call turn around basis to one particular customer or to different customers based on the LATA in which the TFC call originates.

(T)

(T)

Premium TFC Data Base Queries provide instructions to route TFC calls to:

(T)

(A) Different customers based on time of day, day of week, or based on number of calls allocated by TFC subscriber selected percentages.

(T)

(B) Different terminating locations based on time of day, day of week, or based on number of calls allocated by TFC subscriber selected percentages.

(T)

(C) Standard seven digit local exchange telephone numbers at the terminating end based on the TFC subscriber's specific requirements.

(T)

The TFC subscriber is responsible for arranging the entry of the various routing instructions discussed herein into the Number Administration Service Center's (NASC's) Service Management System (SMS).

(T)

Rate regulations and charges applicable to TFC Data Base Query Service appear in 4.5.2(H) and 4.6.3(A).

4.2.20 500 Customer Identification Function

This function provides for screening of the first six digits of all 500-NXX-XXXX type calls generated by end users to determine the customer to which the call is to be routed. This function is provided in conjunction with 500 SAC Access Service and with FGC, FGD, BSA-C and BSA-D. This function is available with Tandem Switch Signaling.

(N)

4.2.21 Tandem Switch Signaling

Tandem Switch Signaling, offered in conjunction with FGD Switched Access, 500 SAC Access, or 900 SAC Access Service with either multifrequency address signaling or SS7 Out of Band Signaling Access Service, provides the Carrier Identification Code (CIC) and the OZZ code or circuit code as described in 4.2.5 (A)(E) to determine the customer and trunk group(s) where traffic will be routed. Rate regulations applicable to Tandem Switch Signaling are found in 4.5.2(N)(6).

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.3 Obligations of the Customer

4.3.1 On and Off-Hook Supervision

The customer facilities shall provide the necessary on and off-hook supervision.

4.3.2 ASR Requirements

The customer shall order all Switched Access as in Section 3, and 4.3.2 and 4.3.3.

ASRs for Entrance Facilities and Direct-Trunked Transport must specify the customer designated location, type of service (e.g., Voice Grade, DS1 or DS3), the channel interface, and any optional arrangements desired. In addition, ASRs for Direct-Trunked Transport must specify any Hubs involved and the end office, when direct routing to an end office is desired, or the Telephone Company access tandem if direct routing to a Telephone Company access tandem switch for purposes of obtaining Tandem-Switched Transport is desired.

ASRs for Direct-Trunked Transport must also specify the Feature Group or BSA, number of lines or trunks at the end office or Telephone Company access tandem, major traffic types and directionality. Ordered quantities shall be specified by originating and terminating direction and by traffic type (e.g., MTS/MTS-type or WATS/WATS-type). Where the customer desires to segregate its originating traffic into separate trunk groups by type of traffic, the customer must specify the ordered quantities by trunk group and by traffic type. For example, if a customer desires a separate trunk group to carry its 500, TFC or 900 traffic, the order must specify the trunks or BHMCs associated with 500, TFC or 900 traffic for that trunk group. (T)

Customers may order Tandem-Switched Transport by specifying the number of trunks required between the CDL and access tandem switch or BHMCs between the CDL and the end office. The customer shall provide, when it orders BHMC, its projected interstate BHMC between the CDL and each end office in the Access Area by traffic type. The customer shall provide, when it orders lines or trunks, its projected interstate traffic distribution by percent for each end office in the Access Area by traffic type. If the customer fails to provide its traffic distribution, the Telephone Company will use appropriate Telephone Company traffic studies to project distribution by end office. (T)

When FGA or BSA-A is ordered the customer shall specify whether or not the terminating traffic is to be restricted to the Access Area as in 4.2.1(A)(6), and 4.5.2(N) or extended beyond the Access Area (i.e., local calling area). If the customer wishes to extend the traffic beyond the FGA or BSA-A Access Area, the rates in 4.5.2(N)(3), will apply. If the customer wishes to restrict the traffic, the rates in 4.5.2(B) may apply, depending upon the optional arrangement selected.

When the Alternate Traffic Routing optional arrangement is provided, Percent Traffic Routed (PTR) values must be provided on the ASR as described in 4.5.2(N)(2)(h).

When a customer orders Switched Access for mixed interstate and intrastate usage, the customer shall provide an estimate of the total usage which will be intrastate by traffic type.

The customer allocated percentages will be used as a basis of the jurisdictional determination for billing purposes of all charges until a more accurate determination can be provided as in 4.3.3 and 4.5.2(J).

4.3.3 Jurisdictional Determination

For purposes of determining the jurisdiction of Switched Access traffic, once the Switched Access service is activated, the following criteria will apply:

- (A) When the Telephone Company has measurement capability to provide the data to determine the jurisdiction of Switched Access traffic, the Telephone Company will determine the jurisdiction of Switched Access traffic. In those instances where the Telephone Company cannot determine the jurisdiction, the customer will be required to provide this information as described following.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.5 Rate and Charge Regulations (Cont'd)

4.5.2 Rate Regulations (Cont'd)

(A) Types of Rates and Charges (Cont'd)

(3) Nonrecurring Charges (Cont'd)

(f) Switched Access Ordering Charges

Switched Access Ordering Charges are associated with the work performed by the Telephone Company in connection with the receiving, recording and processing of customer service requests. There are two types of service ordering charges.

(1) Initial Ordering Charge - Switched Access
(USOC - SESCL)

This charge, applied on a per ASR basis, is associated with the work performed by the Telephone Company in connection with the receiving, recording and processing of service requests. The Switched Access Ordering Charge applies to all requests to establish Entrance Facilities, Direct-Trunked Transport Facilities, and Tandem-Switched Transport Facilities. Where Entrance Facilities and Direct-Trunked and/or Tandem-Switched Transport are ordered on a single ASR, only one Switched Access Ordering Charge applies. This charge is in addition to any Service Installation Charge for Entrance Facility installations.

CenturyTel. of Missouri	\$30.14	(R)
CenturyTel of Central Missouri	97.50	(R)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.5 Rate and Charge Regulations (Cont'd)

4.5.2 Rate Regulations (Cont'd)

(A) Types of Rates and Charges (Cont'd)

(3) Nonrecurring Charges (Cont'd)

(f) Switched Access Ordering Charges (Cont'd)

(2) Subsequent Ordering Charge - Switched Access
(USOC - SESBX)

This charge applies on a per ASR basis for modifications to an existing service. This would include activities such as:

- Changes and/or additions to end office services optional arrangements (changes in hunt group or screening arrangements).
- The combination or splitting of FGA or BSA-A hunt groups.
- A move to a new point of termination within the same CDL.
- A change for rating purposes from one type of Transport to another (i.e., Special to Switched).
- The activation or deactivation of 900 SAC NXX codes on a per tandem level basis.
- The addition of Calling Party Number (CPN) Parameter, Carrier Selection Parameter (CSP), and Charge Number (CN) Parameter when ordered subsequent to the provision of SS7 Out of Band Signaling.
- Changes in FGD or BSA-D switched access and TFC SAC Access signaling from multifrequency address signaling to SS7 Out of Band Signaling except as specified in 4.5.2(G)(1).

CenturyTel of Missouri	\$30.14	(R)
CenturyTel of Central Missouri	97.50	(R)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.5 Rate and Charge Regulations (Cont'd)

4.5.2 Rate Regulations (Cont'd)

(A) Types of Rates and Charges (Cont'd)

(3) Nonrecurring Charges (Cont'd)

(g) Service Rearrangements (Cont'd)

If the change involves only rollovers or grooming, then no charges will apply. A rollover is the retermination of a segment of a lower capacity switched transport entrance facility onto a higher capacity switched transport entrance facility. The rollover must occur in the wire center where the higher capacity service is multiplexed with no other changes to the lower capacity service being reterminated (i.e., the segment must not require rerouting to connect to the multiplexer of the higher capacity service).

Grooming is the retermination of a lower capacity switched transport entrance facility from one channel in a higher capacity switched transport entrance facility to another channel in the same higher capacity service or to another channel in another higher capacity switched transport entrance facility (i.e., change in connecting facility assignment) in the same wire center, with no other changes to the lower capacity service.

(N)

(N)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.5 Rate and Charge Regulations (Cont'd)

4.5.2 Rate Regulations (Cont'd)

(A) Types of Rates and Charges (Cont'd)

(3) Nonrecurring Charges (Cont'd)

(h) Design Change Charge (USOC - H28)

A design change is any change to a pending ASR or a change to an existing service which requires engineering review or change. Design changes may include the addition or deletion of End Office Services Optional Arrangements or changes in the signaling arrangements associated with the Interface Arrangements as described in 4.2.3(B). Design changes do not include a change of Switched Access Interface Arrangement or facility type, IC CDL, end user premises, end office switch, Feature Group or Basic Serving Arrangement type. Changes of this nature will require the issuance of a new ASR and the cancellation of the original ASR with the appropriate cancellation charges applied.

The Telephone Company will review the requested change, notify the customer whether the change can be accommodated and if a new service date is required. If the customer authorizes the Telephone Company to proceed with the design change, a Design Change Charge will apply.

The Design Change Charge for Switched Access Service in Section 4.6.1(C) will apply on a per ASR per occurrence basis for each request requiring a design change.

The Design Change Charge is in addition to any Switched Ordering charges associated with the change requested. When the design change is on a pending ASR, the Initial Ordering Charge - Switched Access will apply. If the design change is to an existing service, the Subsequent Ordering Charge - Switched Access will apply.

If a change of service date is required, the Service Date Change Charge in 3.2.2(A) will also apply.

CenturyTel of Missouri	\$26.21	(R)
CenturyTel of Central Missouri	32.40	(R)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.5 Rate and Charge Regulations (Cont'd)

4.5.2 Rate Regulations (Cont'd)

(A) Types of Rates and Charges (Cont'd)

(3) Nonrecurring Charges (Cont'd)

(i) Installation Charge for FGA or BSA-A Optional Call Blocking Arrangement (USOC – CAH)

-

This charge applies per FGA or BSA-A line equipped with either of the optional call blocking arrangements in Section 4.2.5(D) and (E); InterLATA Call Denial on Line or Hunt Group or Call Denial on Line or Hunt Group outside the Access Area. This charge applies in addition to applicable Switched Access Ordering Charges.

(j) Change of Switched Access Type

Changes from one type of Switched Access to another including the change from Feature Group to Basic Serving Arrangement or the change from Basic Serving Arrangement to Feature Group will be treated as a discontinuance of one type of FIA and start of another. The Switched Access Installation and Ordering Charges will apply, with the following exception:

- (1) When a customer upgrades a FGA, FGB, or FGC to a FGD at the same first point of switching, the charge will not apply. If however, optional features are added to the service at the time the conversion takes place, the Ordering Charge for these additions will apply.
- (2) When a customer upgrades a BSA-A, BSA-B, or BSA-C to a BSA-D at the same first point of switching, the charge will not apply. If however, a BSE(s) are added to the service at the time the conversion takes place, the Switched Access Ordering Charge for these additions will apply.
- (3) Where a customer has Feature Group B (FGB) and Feature Group D (FGD) at a Telephone Company access tandem, the following application of charges will apply for end office conversions:
 - a) Where FGB service exists at an end office the customer may retain the FGB service or upgrade the FGB service to FGD service in conjunction with equal access conversion. When the customer requests no physical changes or trunking additions/deletions to the existing facilities, the ordering charge will not apply to retain the existing service or upgrade.

(N)

(N)

(T)

(N)

(N)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.5 Rate and Charge Regulations (Cont'd)

4.5.2 Rate Regulations (Cont'd)

(A) Types of Rates and Charges (Cont'd)

(3) Nonrecurring Charges (Cont'd)

(j) Change of Switched Access Type (Cont'd)

(3) (Cont'd)

- b) Where FGB and/or FGD service exists at a Telephone Company access tandem but does not exist at an end office and the customer now wants to add FGB and/or FGD to the end office, the ordering charge will not apply to add the service when the customer requests no physical changes, additions, or deletions to the customer's existing facilities.
- c) Where FGB and/or FGD service exists at a Telephone Company access tandem and FGB also exists at the end office and the customer wants to retain the FGB service but add FGD service with equal access conversion, the ordering charge will not apply to add the FGD service when the customer requests no physical changes, additions, or deletions to the customer's existing facilities.

(4) Where a customer has BSA-B and BSA-D at a Telephone Company access tandem, the following application of charges will apply for end office conversions:

- a) Where BSA-B service exists at an end office the customer may retain the BSA-B service or upgrade the BSA-B service to BSA-D service in conjunction with equal access conversion. When the customer requests no physical changes or trunking additions/deletions to the existing facilities, the ordering charge will not apply to retain the existing service or upgrade.
- b) Where BSA-B and/or BSA-D service exists at a Telephone Company access tandem but does not exist at an end office and the customer now wants to add BSA-B and/or BSA-D to the end office, the ordering charge will not apply to add the service when the customer requests no physical changes, additions, or deletions to the customer's existing facilities.

(N)

(N)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.5 Rate and Charge Regulations (Cont'd)

4.5.2 Rate Regulations (Cont'd)

(A) Types of Rates and Charges (Cont'd)

(3) Nonrecurring Charges (Cont'd)

(j) Change of Switched Access Type (Cont'd)

(N)

(4) Cont'd

- b) Where BSA-B and/or BSA-D service exists at a Telephone Company access tandem but does not exist at an end office and the customer now wants to add BSA-B and/or BSA-D to the end office, the ordering charge will not apply to add the service when the customer requests no physical changes, additions, or deletions to the customer's existing facilities.
- c) Where BSA-B and/or BSA-D service exists at a Telephone Company access tandem and BSA-B also exists at the end office and the customer wants to retain the BSA-B service but add BSA-D service with equal access conversion, the ordering charge will not apply to add the BSA-D service when the customer requests no physical changes, additions, or deletions to the customer's existing facilities.

(N)

(k) Moves

(M,C)

A move involves a change in the physical location of the point of termination of Switched Access. A move normally involves an interruption of Switched Access for the period required to complete the move. The charge for the move depends on whether the move is within the same CDL or to a different CDL.

(1) Same CDL

When the move is to a new point within the same CDL (same address and/or same building), the Switched Access Ordering Charge in 4.6.1(B) will apply. There will be no change in the minimum period requirements. For services subject to payment plan regulations the same payment plan will remain in force.

(2) A Different CDL

When the move is to a different CDL or to an EIS as described in Section 17, it will be treated as a disconnect and an installation of Switched Access. The Switched Access Installation and Ordering charges, as specified in 4.6.1(B) will apply to the Switched Access, installed at the CDL. A new minimum period will be established for the installed Switched Access. The customer will remain responsible for all remaining minimum period charges associated with the disconnected Switched Access Service. For services subject to payment plan regulations the same payment plan will remain in force.

(M,C)

(M) This material previously appeared as (F) on Sheet 134.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.5 Rate and Charge Regulations (Cont'd)

4.5.2 Rate Regulations (Cont'd)

(B) (Reserved for Future Use

(C) (Reserved for Future Use

(D) (Reserved for Future Use

(E) (Reserved for Future Use

(C)

(M)

(F) (Reserved for Future Use)

(C)

(M1)

(M) Material omitted from Sheet 133 as (E) now appears on Sheets 133,133.1 and 133.2 as (j).

(M1) Material previously appearing as (F) on Sheet 134, now appears as (k) on Sheet 133.2.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.5 Rate and Charge Regulations (Cont'd)

4.5.2 Rate Regulations (Cont'd)

(F) (Reserved for Future Use)

(C)

(M)

(M)

(G) Signaling System 7 (SS7) Out of Band Signaling

- (1) Subsequent Ordering Charges - Switched Access will apply for a change in FGD or BSA-D switched access and 800/888/877 SAC Access signaling from multifrequency address signaling to SS7 Out of Band Signaling except as specified in 4.5.2(G)(1).
- (2) Switched access ordering charges will not apply if Calling Party Number (CPN) Parameter, Carrier Selection Parameter (CSP), and/or Charge Number (CN) Parameter are ordered at the same time as SS7 Out of Band Signaling is ordered in conjunction with FGD or BSA-D. Subsequent Ordering Charges - Switched Access will apply if these optional features are ordered subsequent to the provision of SS7 Out of Band Signaling.

(H) TFC Data Base Query Service

(T)

Query usage charges for TFC Data Base Query Service shown in 4.6.3(A) apply as follows:

(T)

- (1) A Basic TFC Data Base Query charge will apply for each basic TFC call query received at the Telephone Company's TFC data base. Per query charges are accumulated over a monthly period and billed to the customer on a monthly basis.
- (2) A Premium TFC Data Base Query charge will apply for each premium TFC call query received at the Telephone Company's TFC data base. Per query charges are accumulated over a monthly period and billed to the customer on a monthly basis.

(T)

(T)

(T)

(T)

(M) Material omitted from this sheet now appears on sheet 133.2.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.5 Rate and Charge Regulations (Cont'd)

4.5.2 Rate Regulations (Cont'd)

(N) Description and Application of Rates (Cont'd)

(1) Determination of Premium Rates (Cont'd)

The specific application of premium rates for a specific customer is dependent upon the feature group or Basic Serving Arrangement, and the availability of equal access capabilities in the end office or the WATS Serving Office to which the service is provided. The Entrance Facility, Direct-Trunked Transport, Tandem-Switched Transport and Multiplexing rate elements are not subject to premium rating.

Premium rates apply to all FGC, FGD, BSA-C and BSA-D access minutes; to all FGA, FGB, BSA-A, BSA-B and SAC Access Service access minutes that originate from or terminate at end offices or WATS Serving Offices equipped with equal access (i.e., FGD, BSA-D) capabilities; and to all FGB or BSA-D access minutes that terminate at end offices not equipped with equal access, when the service is provided to customers who furnish MTS and WATS. Premium rates also apply to switched access minutes that originate or terminate at a Wireless Switching Office (WSO) directly interconnected to a Telephone Company access tandem office. (T)

Premium rates apply to all FGA, FGB, BSA-A, BSA-B and SAC Access Service access minutes (measured or assumed) that originate from or terminate at end offices or WATS Serving Offices which are not equipped with equal access capabilities.

Premium rates also apply to switched access minutes of use that originate/terminate at a WSO directly interconnected to a Telephone Company nonequal access type end office. (T)

(2) Switched Transport

The Switched Transport is determined as follows:

- (a) The Tandem-Switched Transport - Facility rate is applied per access minute per airline mile for each Switched Access Feature Group or Basic Serving Arrangement type. Tandem-Switched Transport - Facility airline mileage will be determined as follows:

Where Direct-Trunked Transport is ordered between a serving wire center and an access tandem, and Tandem-Switched Transport is ordered to subtending end offices, mileage will be measured from the access tandem to the end office or WSO (for WATS and WATS-type).

When the end office is acting as a host office, a separate mileage calculation determines the mileage from the host office to the remote office. Traffic originating from and/or terminating to the remote will be billed Tandem-Switched Transport charges. The Tandem Switching charge does not apply to traffic between a host and remote office.

The V&H coordinate method is used to determine the actual mileage as set forth in NECA, Inc.'s Tariff FCC No. 4(*). If the calculated miles include a fraction, the value is rounded up to the next full mile.

(*) For intraLATA LEC to LEC traffic, percentages of ownership will be determined by the V&H coordinates located in the Missouri Intrastate IntraLATA Compensation Plan Database.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.5 Rate and Charge Regulations (Cont'd)

4.5.2 Rate Regulations (Cont'd)

(N) Description and Application of Rates (Cont'd)

(2) Switched Transport (Cont'd)

- (e) The Entrance Facility rate is a flat-rated charge assessed per Voiceband, DS1 or DS3 termination at the CDL. This charge will apply even if the CDL and the serving wire center are co-located in a Telephone Company building.

For DS1 Entrance Facilities, a "First System" charge is assessed per Entrance Facility for the first DS1 ordered. When the same customer requests additional DS1 service on the same ASR to be installed at the same time between the same CDL and serving wire center, the "Additional System" charge will apply.

- (f) The Tandem Switching rate is usage-sensitive and is applied per access minute to all feature groups for Tandem-Switched Transport with three exceptions. The Tandem-Switching Rate is not applicable for Tandem-Switched Transport between a host office and a remote office, nor is it applicable for FGA or BSA-A.

The Tandem Switching rate also will not apply to access minutes that originate or terminate at the end office part of a Class 4/5 switch.

(D)

(D)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.5 Rate and Charge Regulations (Cont'd)

4.5.2 Rate Regulations (Cont'd)

(N) Description and Application of Rates (Cont'd)

(4) (Reserved for Future Use)

(C)

(D)

(D)

(5) End Office Switching

End Office Switching is available on a bundled or unbundled basis. End Office Switching - Bundled (EOSB) rates apply to Switched Access services provided as Feature Groups. End Office Switching - Unbundled (EOSU) rates apply to Switched Access services provided as Basic Serving Arrangements.

When equal access becomes available, rates for end office switching 1 (EOS1) and end office switching 2 (EOS2) will apply as follows:

- (a) FGA and BSA-A customers will pay the EOS1 rate for all FGA or BSA-A access minutes originating from or terminating at that end office except as in (f).
- (b) FGB and BSA-B customers with no FGD or BSA-D service provided at the same end office will pay the EOS1 rate for all FGB or BSA-B or access minutes originating from or terminating at that end office except as in (f).
- (c) FGB and BSA-B customers with FGD or BSA-D service provided at the same end office will pay the EOS1 rate for FGB or BSA-B access minutes originating from that end office and the EOS2 rate for FGB or BSA-B access minutes terminating at that end office.
- (d) FGD and BSA-D customers will pay the EOS2 rate for all FGD or BSA-D access minutes originating from or terminating at that end office.
- (e) SAC Access Service customers will pay the EOS2 rate for all SAC Access minutes originating from that end office.
- (f) When FGA, FGB, BSA-A or BSA-B is used for terminating WATS or WATS-type services, the customer will pay the EOS2 rate for all terminating access minutes.
- (g) End Office Switching rates do not apply to switched access minutes of use that originate or terminate at MTSOs directly interconnected to a Telephone Company access tandem office.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.5 Rate and Charge Regulations (Cont'd)

4.5.2 Rate Regulations (Cont'd)

(N) Description and Application of Rates (Cont'd)

(6) Tandem Switch Signaling (Cont'd)

If the TSS customer fails to provide the call detail information or fails to provide information in the required format within 30 days from the call activity date, then the TSS customer will be billed for that day's usage. Where the total usage measured by the Telephone Company differs from the total amount of usage provided by the TSS customer's call detail information, the Telephone Company will work cooperatively with the TSS customer to resolve the discrepancies.

The Telephone Company reserves the right to audit billing tape information upon 30 days' notice to the TSS customer. In the event of a discrepancy, if final agreement cannot be reached, charges will be billed based on the results of the audit.

(7) Dedicated Trunk Port Charge

The Dedicated Trunk Port charge, as set forth in 4.6.2(I), shall apply for termination of a dedicated trunk at the access tandem or an end office. It is flat-rated and is assessed per voice grade or DS1 channel terminating at an end office or access tandem.

(8) Shared Trunk Port Charge

The Shared Trunk Port, as set forth in 4.6.3(O), provides for the termination of a Tandem-Switched Trunk at an end office. The Shared Trunk Port is usage rated and shall be assessed to all access minutes which utilize Tandem-Switched Transport. This includes minutes of use associated with FGA service when traffic is terminated in an end office that is not the dial tone office and on minutes of use provided at a remote office.

The Shared Trunk Port charge will not apply to access minutes that originate or terminate at the end office part of a Class 4/5 switch.

The Shared Trunk Port charge does not apply to switched access minutes of use that originate or terminate at MTSOs directly interconnected to a Telephone Company access tandem.

When the Tandem-Switched Transport is provided by more than one telephone company, the Shared Trunk Port charge shall be billed by the Telephone Company in whose territory the end office is located, as in 2.7(A)(2)(g).

(N)

(N)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.5 Rate and Charge Regulations (Cont'd)

4.5.2 Rate Regulations (Cont'd)

(O) Measuring Access Minutes (Cont'd)

(5) Feature Group D and BSA-D Usage Measurement (Cont'd)

For terminating calls over FGD or BSA-D with MF signaling or FGD or BSA-D with SS7 Out of Band Signaling, usage measurement begins when the FGD or BSA-D first point of switching receives answer supervision from the end office switch, indicating the terminating end user has answered.

The measurement of terminating call usage over FGD or BSA-D with MF signaling ends when the FGD or BSA-D first point of switching receives disconnect supervision from either the end office switch, indicating the terminating end user has disconnected, or the CDL, whichever is recognized first by the first point of switching.

The measurement of terminating call usage over FGD or BSA-D with SS7 Out of Band Signaling ends when the FGD or BSA-D first point of switching receives or sends a Release Message, whichever occurs first.

(6) SAC Access Service Usage Measurement

SAC Access Service usage measurement shall be in accordance with the regulations set forth for FGC, FGD, BSA-C and BSA-D. Specifically, for usage originating from end offices not equipped with equal access capabilities, access minutes shall be measured in the same manner in which FGC or BSA-C access minutes are measured. For usage originating from end offices equipped with equal access capabilities, access minutes shall be measured in the same manner in which FGD or BSA-D access minutes are measured.

(7) Usage Measurement Not Available for FGC, BSA-C, FGD and BSA-D

In the even the customer message detail is not available because the Telephone Company lost or damaged tapes or experienced recording system outages, the Telephone Company will estimate the volume of lost customer access minutes of use based on previous actual recorded usage.

(N)
|
(N)

(P) FGD and BSA-D Switched Access Service With 950-XXXX Access

When a customer orders FGD or BSA-D Switched Access Service with 950-XXXX Access, as described in 4.2.5(T), to be included with the installation of new FGD or BSA-D switched access facilities, appropriate Switched Access Installation Charges and Switched Access Ordering Charges will apply for the installation of the new FGD or BSA-D switched access facilities.

When a customer orders FGD or BSA-D Switched Access Service with 950-XXXX Access to be added to an existing FGD or BSA-D switched access service, only the Subsequent Ordering Charge - Switched Access and the Design Change Charge will apply for the addition of this optional end office service arrangement.

4.5.3 (Reserved for Future Use)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.6 Rates and Charges

4.6.1 Nonrecurring Charges

(A) (Reserved for Future Use)

(B) Switched Access Service Ordering Charges

	<u>USOC</u>	CenturyTel of <u>Central Mo.</u>	Century Tel of <u>Missouri</u>	
Initial – Per ASR	SESCL	\$97.50 (R)	\$30.14 (R)	(C)
Subsequently – Per ASR	SESBX	97.50 (R)	30.14 (R)	(C)

(C) Design Change Charge

- <u>Per ASR/Per Occurrence</u>		32.40 (R)	26.21 (R)	(C)
---------------------------------	--	-----------	-----------	-----

(D) (Reserved for Future Use)

(M)

(M)

(E) 500 NXX Translation Charge
– Per ASR/Per End Office

(T)

First NXX	NW51X	23.00	23.00	
East Additional NXX	NW5AX	12.00	12.00	(T)

(M) Material omitted from this sheet now appears on Sheet 152.1

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.6 Rates and Charges (Cont'd)

4.6.2 Switched Transport

		<u>Rate</u>	
		<u>Originating</u>	<u>Terminating</u>
(A)	<u>Tandem-Switched Transport – Facility</u> Per Access Minute, Per Airline Mile		
	CenturyTel of Central Missouri	\$0.0000260	\$0.0000260
	CenturyTel of Missouri, LLC	\$0.0000346	\$0.0000346
(B)	<u>Tandem-Switched Transport – Termination</u> Per Access Minute, Per Termination		
	CenturyTel of Central Missouri	\$0.0002888	\$0.0002888
	CenturyTel of Missouri, LLC	\$0.0001430	\$0.0001430
(C)	<u>Tandem Switching</u> Per Access Minute		
	CenturyTel of Central Missouri	\$0.0022365	\$0.0022365
	CenturyTel of Missouri, LLC	\$0.0014957	\$0.0014957
(D)	<u>Shared Multiplexing</u> Per Access Minute		
	CenturyTel of Central Missouri	\$0.0001810	\$0.0001810
	CenturyTel of Missouri, LLC	\$0.0000368	\$0.0000368
(E)	<u>Interconnection Rate</u> Telephone Company Provided Transport		
	CenturyTel of Central Missouri	\$0.000225	\$0.000000 (R)
	CenturyTel of Missouri, LLC	\$0.012188	\$0.000000 (R)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.6 Rates and Charges (Cont'd)

4.6.3 End Office Services

	<u>USOC</u>	CenturyTel of <u>Central Mo.</u>	Century Tel of <u>Missouri</u>	(T)
(A) Basic TFC Data Base Query Charge		\$0.00992551	\$0.00992551	
(B) <u>End Office Switching - Bundled (EOSB)</u>				
Per Access Minute				
<u>Premium EOS1</u>				
Originating		0.02542121	0.02542121	(T)
Terminating		0.00309600	0.00199500	(R)
<u>Premium EOS2</u>				(T)
Originating		0.02794254	0.02794254	(T)
Terminating		0.00309600	0.00199500	(R)
(C) <u>End Office Switching Unbundled (EOSU)</u> <u>- Circuit Switched Line</u>				(T)
Per Access Minute				
<u>Premium EOS1</u>				
Originating		0.02542121(l)	0.02542121 (l)	(C)
Terminating		0.00309600	0.00199500	(R)
<u>Premium EOS2</u>				(T)
Originating		0.02794254	0.02794254	(T)
Terminating		0.00309600	0.00199500	(R)

(M)
|
(M)

(M) Material omitted from this sheet now appears on Sheet 152.0.1

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.6 Rates and Charges (Cont'd)

4.6.3 End Office Services

	<u>USOC</u>	<u>CenturyTel of Central Mo.</u>	<u>Century Tel of Missouri</u>	<u>(T)(M)</u>
(D) <u>End Office Switching - Unbundled - Circuit Switched Trunk</u>	(EOSU)			
Per Access Minute				
<u>Premium EOS1</u>				
Originating		\$0.02542101	\$0.02542101	(T)
Terminating		0.00309600	0.00199500	(R)
<u>Premium EOS2</u>				(T)
Originating		0.02794254	0.02794254	(T)
Terminating		0.00309600	0.00199500	(R)
(E) <u>Alternate Traffic Routing - BSE Premium Nonrecurring Charge Per Trunk Group Equipped</u>	(CF3AR)			
		\$67.09	\$67.09	(R)(M)

(M) This material previously appeared on Sheet 152.

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.6 Rates and Charges (Cont'd)

4.6.3 End Office Services (Cont'd)

(F) Automatic Number Identification (ANI) - BSE

Rate
Per ANI Attempt

\$.00014000

(R)

	<u>USOC</u>	<u>CenturyTel of Central Mo.</u>	<u>Century Tel of Missouri</u>	
(G) <u>User Transfer – BSE</u>	(EO3)			(T)
<u>Monthly Rate</u> <u>Per Line Arranged</u>		\$1.50	\$1.12 (R)	
(H) <u>Hunt Group Arrangement-BSE</u>	(CF3HG)			(T)
<u>Premium Monthly Rate</u> <u>Per Line Equipped</u>		3.00	0.07	(I)
(I) <u>Queuing – BSE</u>	(CF3QU)			
<u>Premium Monthly Rate</u> <u>Per Group Equipped</u>		15.00	4.65	(R)
(J) <u>Uniform Call Distribution – BSE</u>	(CF3UD)			
<u>Premium Monthly Rate</u> <u>Per Line Equipped</u>		5.00	5.00	(R)
(K) <u>Network Blocking Charge</u>				(M)
Applies to FGB, FGC, FGD, BSA-B, BSA-C, BSA-D SAC Access Service - Per Call		0.0180	0.0100 (R)	(M)(C)

(M) This material previously appeared on Page 150

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.6 Rates and Charges (Cont'd)

4.6.3 End Office Services (Cont'd)

	<u>USOC</u>	CenturyTel of <u>Central Mo.</u>	Century Tel of <u>Missouri</u>	(T)
(L) <u>Remote Call Forwarding – BSE</u> (FOMPX)				(T)
Premium Monthly Rate Per DID Term		\$16.00	\$1.63	(R)
(M) <u>Direct Inward Dialing (DID) – BSE</u>				
Monthly Rate				
Per DID Term (NDT)		35.00	11.90	(R)
Per Block of 20 Numbers (ND4)		18.00	2.62	(R)
(N) <u>Billed Number Screening (BNS) - BSE</u>				
Monthly Rate				
Per Lines Screened (RTVXQ)		4.10	0.33	(R)
(O) <u>Shared Trunk Port</u>				(T)
Per Access Minute				
Originating		0.0027245	0.0004466	
Terminating		0.0027245	0.0004466	(T)
(P) <u>Dedicated Trunk Port</u>				
Per Port				(N)
Voice		27.29	22.47	
DS1		10.14	8.39	(N)

FACILITIES FOR INTRASTATE ACCESS

4. SWITCHED ACCESS (Cont'd)

4.6 Rates and Charges (Cont'd)

4.6.4 (Reserved for Future Use)*

(C)

(D)

(D)

4.6.5 FGA or BSA-A Usage Sensitive Credit Allowance

Usage Sensitive Service
Credit Allowance
Credit Per Originating FGA or BSA-A Access Minute #

CenturyTel of Central Missouri \$.00049351

4.6.6 Assumed Minutes of Use Monthly Surrogate

<u>Per Two Way</u> <u>Line/Trunk</u>	<u>Per One Way</u> <u>Line/Trunk</u>	
	<u>Originating</u> <u>Only</u>	<u>Terminating</u> <u>Only</u>
	<u>FGA or FGB or</u> <u>BSA-A BSA-B</u>	<u>FGA or FGB or</u> <u>BSA-A BSA-B</u>
2451 (1)	(1) (1)	(1) (1)

4.6.7 Carrier Identification Parameter (CIP)

<u>Non-Recurring</u> <u>Charge-Per CIC.</u> <u>Per End Office</u> <u>Direct Trunk</u> <u>Group</u>	<u>Non-Recurring</u> <u>Charge Per CIC.</u> <u>Per Access Tandem</u> <u>Charges</u> <u>Per Trunk</u>	<u>Monthly Recurring</u>
<u>Direct Trunk</u> <u>Group</u>	<u>Direct Trunk</u> <u>Group</u>	
\$80.00	\$1,120.00	\$.45657589

* The Information Surcharge has been eliminated.
The credit is applied to the End Office Switching rate element.
(1) These jurisdictions either have all existing services measured or have no customers at this time. In the event an ASR is received for a new customer and there is no measurement capability for the office requested, a traffic study will be made to establish a surrogate and such surrogate will be tariffed.

FACILITIES FOR INTRASTATE ACCESS

12. CARRIER COMMON LINE SERVICE (Cont'd)

12.5 Rates and Charges

Rates for Carrier Common Line Service are as follows:

	CenturyTel of <u>Central Mo.</u>	Century Tel of <u>Missouri</u>	(T)
Premium Rate Per Access Minute			
Originating	\$0.01060799	\$0.010608	(T)
Terminating	0.00000000	0.000000	(R)